

CSX EDI 998 Set Cancellation/Void

Version: 005030

Questions about the CSX EDI 410 Implementation Guide should be directed to:

877-SHIPCSX option 2, prompt 2

Monday - Friday: 7:00 AM - 6:00 PM

Publication: September 2007

Table of Contents

998	Set Cancellation
	Transaction Set Header
ZD	Transaction Set Deletion - ID. Reason, and Source
SE	

998

Set Cancellation

Functional Group=AL

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Set Cancellation Transaction Set (998) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to request the deletion of a previously transmitted transaction set and will indicate the reason for this action, such as diversion or cancelled bill.

Heading:

<u>Pos</u>	<u>ld</u>	Segment Name	Req	Max Use	Repeat	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1		N1/0100	Must use
0200	ZD	Transaction Set Deletion - ID, Reason, and Source	М	1			Must use
0300	SE	Transaction Set Trailer	M	1			Must use

Notes:

1/0100 998s received after a unit has ingated will not be processed. An 824 will be sent to the sender of a 998 stating whether the void was processed or not. If you company cannot process an 824, the 824 can be converted to an email and sent to the address you identify.

Accepting the 824 or email equivalent is required for all 998 senders.

ST Transaction Set Header

Pos: 0100 Max: 1 Heading - Mandatory Loop: N/A Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

Ref	<u>ld</u>	Element I	<u>Name</u>	Req	<u>Type</u>	Min/Max	<u>Usage</u>	
ST01	143	Transaction Set Identifier Code		М	ID	3/3	Must use	
		Description: Code uniquely identifying a Transaction Set						
		<u>Code</u>	<u>Name</u>					
		998	Set Cancellation					
ST02	329	Transacti	on Set Control Number	M	AN	4/9	Must use	
		Description of the difference and all acceptants that accept he continue within the transportion and						

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

- 1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
- The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

ZD Transaction Set Deletion - ID, Reason, and Source

Pos: 0200 Max: 1 Heading - Mandatory Loop: N/A Elements: 8

User Option (Usage): Must use

Purpose: This segment is used to specify the transaction set to be canceled

Element Summary:

Ref ZD01	<u>ld</u> 143	Element Name Transaction Set Identifier Code	Req M	Type ID	Min/Max 3/3	<u>Usage</u> Must use				
		Description: Code uniquely identifying a Transaction Set								
		CodeName404Rail Carrier Shipment Information	on							
ZD02	145	Shipment Identification Number	0	AN	1/30	Used				
		Description: Identification number assigned to the shipment by the shipper that uniquely identifies the shipment from origin to ultimate destination and is not subject to modification; (Does not contain blanks or special characters)								
ZD03	206	Equipment Initial	М	AN	1/4	Must use				
		Description: Prefix or alphabetic part of an ed	quipmen	t unit's id	entifying numb	er				
ZD04	207	Equipment Number	М	AN	1/15	Must use				
		Description: Sequencing or serial part of an eform for equipment number is preferred) CSX Note 1: Do not include a check of 998 failing to process.								
ZD05	244	Transaction Reference Number	0	AN	1/50	Used				
Description: Sender's assigned number for referenced transaction set CSX Note 1: For bill of lading cancellations (voids), the bill of lading numner from teh shippers original 404 (N9*BM*BOLNUMBER) is required.										
ZD06	243	Transaction Reference Date	0	DT	8/8	Used				
		Description: Date of referenced transaction set expressed in format CCYYMMDD where CC represents the first two digits of the calendar year CSX Note 1: Date of the sender's original 404.								
ZD07	202	Correction Indicator	М	ID	2/2	Must use				
		Description: Code used to indicate that the transaction set contains information which corrects previous information All valid standard codes are used.								
ZD08	140	Standard Carrier Alpha Code	0	ID	2/4	Used				
		Description: Standard Carrier Alpha Code CSX Note 1: Valid SCACs are CSXI (or CS>	K T						

Semantics:

^{1.} ZD09 is the equipment check digit for the equipment number in ZD04.

SE Transaction Set Trailer

Pos: 0300 Max: 1 Heading - Mandatory Loop: N/A Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

Ref	<u>ld</u>	Element Name	Req	Type	Min/Max	<u>Usage</u>		
SE01	96	Number of Included Segments	M	N0	1/10	Must use		
		Description: Total number of segments include segments	led in a	transactio	on set includin	g ST and SE		
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use		
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Comments:

1. SE is the last segment of each transaction set.